


PACSystems™ RX3i

CANopen MASTER
(IC695CNM001)



Introduction

The CNM001 module allows the RX3i Controller CPU to send and receive data on a CANopen network. It can act as master for up to five devices on the CANopen network.

The module's three LEDs display its operating and communications status. A 9-pin male D-connector interfaces to the CANopen network.

A CNM001 module can be installed in any I/O slot in the main rack in an RX3i system except slot 0, or the expansion slot.

Features

- TX PDO data scanning of up to 272 bytes (Includes 20 bytes of module status and slave status diagnostics.)
- RX PDO data scanning of up to 272 bytes
- Fault logging for loss or addition of CANopen slave devices that support Node Guarding, Heartbeat protocol, or have PDO counter health status monitoring enabled.
- Slave status bit per slave address to indicate in reference memory whether devices are healthy. (For devices that support either Node Guarding or Heartbeat protocol, or have PDO counter health status monitoring enabled)

Note: In the CANopen protocol, “transmit” and “receive” are defined from the slave’s point of view. This means that TX PDOs are mapped to the CPU as %AI input scan data and RX PDOs are mapped as %AQ output scan data.

Firmware Upgrades

The CNM001 module receives its firmware upgrades directly from the SYCON.net software using the USB port on the module.

CNM001 Module Specifications

| Specification | Description |
|-------------------------------|---|
| Mounting Location | RX3i main rack: Any slot except slot 0 or expansion slot. |
| Backplane Current Consumption | 800mA at 3.3VDC |
| Hot swappable | Yes |
| RX3i CPU requirements | RX3i CPU Firmware version 7.70 or later |

For product standards, product standards, general operating specifications and installation requirements, refer to the PACSystems RX3i System Manual GFK-2314.

Communications Specifications

| Specification | Description |
|---|---|
| Maximum input data scanned by CPU | 272 bytes (Includes 20 bytes of module status and slave status diagnostics) |
| Maximum output data scanned by CPU | 272 bytes |
| Maximum number of supported slave devices | 5 |
| Maximum number of receive PDOs | 15 |
| Maximum number of transmit PDOs | 30 |
| Exchange of process data | Via Process Data Object (PDO) protocol transfer (synchronized, remotely requested and event driven (change of state)) |
| Functions | Node guarding / life guarding Heartbeat protocol PDO mapping Synchronization Object (SYNC) protocol (producer) |
| Baud rates | 10 kbits/s to 1 Mbits/s |
| Data transport layer | CAN Frames |

| Specification | Description |
|----------------|-------------|
| CAN Frame type | 11 Bit |

For product standards, general operating specifications, and installation requirements, refer to the PACSystems RX3i System Manual, GFK-2314.

Product Documentation

PACSystems RX3i CANOpen Master Module User's Manual, GFK-2831
 PACSystems RX3i CANOpen Master Module Quick Start Guide, GFK-2832

For user manuals, product updates and other information go to the Support website, <https://www.emerson.com/Industrial-Automation-Controls/support> and refer to Controllers and IO, RXi Controllers.

Functional Compatibility

| Subject | Minimum Version Required |
|---------------------------------|--|
| Programmer version requirements | PAC Machine Edition Logic Developer, Release 7.00 |
| CPU version requirements | RX3i CPU firmware version 7.70 on these CPU models: IC695CPE305, IC695CPE310, IC695CPU315, IC695CPU320 IC695CRU320 (including -QP) |

Operational Notes

The CNM001 Master module implements the CANOpen master protocol. For this release of the CANOpen Master module, there are certain exceptions and special notes for operation, as listed below.

| Subject | Description |
|---------------------------------|---|
| Special CANOpen operation | The CNM001 module supports RX PDO data scanning of up to 272 bytes. TX PDO data scanning of up to 252 bytes. up to 5 slave devices. a maximum of 15 receive PDOs. a maximum of 30 transmit PDOs. The CNM001 module does not support multiple masters. |
| Configuring the CANOpen module | The CNM001 Master Module is configured in PAC Machine Edition as a 3rd Party module. |
| Configuring the CANOpen network | A USB Mini Type B connector is used to download the CANOpen network configuration from the SYCON.NET software to the module. The module is not configured through the RX3i backplane.. |
| Upgrading module firmware | Firmware for the CANOpen Master module is upgraded over the USB Mini Type B connector using the SYCON.NET software. This release does not support firmware upgrade through the RX3i CPU and backplane. |

Release History

| Catalog No. | Firmware Version | Date | Comments |
|----------------|------------------|------------|--|
| IC695CNM001-CA | 2.11 | Sep-2019 | Following Emerson's acquisition of this product, changes have been made to apply appropriate branding and registration of the product with required certification agencies. No changes to material, process, form, fit or functionality. |
| IC695CNM001-BA | 2.11 | June 2017 | Address HW component obsolescence and updated agency compliance labeling to add WEEE. No changes to form, fit, or function. |
| IC695CNM001-AA | 2.11 | March 2013 | Initial release. |

Additional Information

PACSystems RX3i User Manuals

PACSystems RX3i and RX7i CPU Reference Manual, GFK-2222

PACSystems RX3i System Manual, GFK-2314

PACSystems RX3i CANopen Master Module User's Manual, GFK-2831

PACSystems RX3i CANopen Master Module Quick Start Guide, GFK-2832

For user manuals, product updates and other information go to the Support website,

<https://www.emerson.com/Industrial-Automation-Controls/support> and refer to *Controllers and IO, RX3i Controllers*.

Technical Support & Contact Information

Home link: <http://www.Emerson.com/Industrial-Automation-Controls>

Knowledge Base: <https://www.emerson.com/Industrial-Automation-Controls/support>

Note: If the product is purchased through an Authorized Channel Partner, please contact the seller directly for any support.

Emerson reserves the right to modify or improve the designs or specifications of the products mentioned in this manual at any time without notice. Emerson does not assume responsibility for the selection, use or maintenance of any product. Responsibility for proper selection, use and maintenance of any Emerson product remains solely with the purchaser.

© 2019 Emerson. All rights reserved.

Emerson Terms and Conditions of Sale are available upon request. The Emerson logo is a trademark and service mark of Emerson Electric Co. All other marks are the property of their respective owners

