

Mini Pocket MultiMeter

Autoranging with 10 functions including Frequency, Capacitance, and Duty cycle

Features:

- Large high contrast 4000 count LCD display
- Auto Power off to conserve battery life
- Autoranging with Relative and Data Hold
- Diode Test and Continuity Beeper
- Built-in storage compartment for integrated test leads
- Protective rubber holster provides extra protection on the meter
- Over-range and low battery indication
- Complete with test leads, protective holster, one CR 2032 button battery and carrying case


Applications:

- Home wiring projects
- Testing electrical systems on cars and boats
- Hobby projects



CE **CAT II-600V**

Specifications	Range	Max. Resolution	Basic Accuracy (%rdg+digits)
DC Voltage:	500V	0.1mV	±(1.3% + 3d)
AC Voltage:	500V	1mV	±(2.3% + 5d)
DC Current	400.0mA	0.01mA	±(2.0% + 5d)
AC Current	400.0mA	0.01mA	±(2.5% + 10d)
Resistance:	400 to 40MΩ	0.1Ω	±(2.0% + 5d)
Capacitance:	200µF	0.001nF	±(3.0% + 15d)
Frequency:	9Hz to 10MHz	0.001Hz	±(2% + 5d)
Duty Cycle:	0.1% to 99.9%	0.1%	±(2% + 5d)
Diode Test:	Test Current at 0.6mA		
Continuity Test:	Audible beep <60		
Dimensions:	4.25 x 2.2 x 0.5" (108 x 56 x 11.5mm)		
Weight:	1.7oz (50g)		



Pocket sized meter includes pouch case

Ordering Information:

DM110.....Mini Pocket MultiMeter



EXTECH INSTRUMENTS CORPORATION
285 Bear Hill Road, Waltham, MA 02451-1064
Phone: 781-890-7440 • FAX 781-890-7864
ISO 9001:2000 CERTIFIED

"Make mine an Extech!™"
www.extech.com

02/14/06 - R1

Copyright © 2006 Extech Instruments Corporation. All rights reserved including the right of reproduction in whole or in part in any form.