



## HOBO® S-CIA-CM14 Sensor

### 12-bit 4-20mA Input Adapter Sensor

The 12-bit 4-20 mA Input Adapter interfaces with any sensor providing a 4-20 mA signal to connect to smart sensor compatible HOBO stations. This adapter features both a non-switched input and a battery-saving switched input that extends the life of external batteries. It also provides a trigger signal for controlling power to attached external sensors, while offering digital filtering which improves measurement accuracy with 32 readings/sample and 60 Hz noise rejection.



#### Key Advantages:

- 12-bit resolution
- Digital filtering improves measurement accuracy with 32 readings/sample—4-20 mA adapter has 60 Hz noise rejection
- Measurement averaging over logging interval further enhances accuracy
- Plug-in modular connector for easy interface with HOBO® stations
- Screw terminal for connecting to sensors
- HOBO RX3000 and U30 stations have room for two adapters
- Use with HOBO USB Micro Station and HOBO MicroRX Station requires Smart Sensor Consolidator Box (S-ADAPT-6) and an extension cable.
- Represents one data input channel

## HOBO S-CIA-CM14 Sensor Specifications

**Measurement range:** 4-20 mA (measures down to 0 mA to detect error condition)

**Operating temperature range:** -40° to 75°C (-40° to 167°F)

**Accuracy:**  $\pm 40 \mu\text{A} \pm 0.3\%$  of reading (over operating temperature range)

**Resolution:**  $\pm 4.93 \mu\text{A}$

**Input impedance:** 124 ohms (differential input)

**Sensor trigger source:** Voltage: 2.5 V  $\pm 2.4\%$ ; maximum current: 1 mA

**Warm-up time:** 300 ms  $\pm 3\%$  (fixed)

**Measurement time:** 16.6 ms  $\pm 3\%$  to filter out 60 Hz noise

**Cable length:** 14 cm (5.5 inch)

## Contact Us

Sales (8am to 5pm ET, Monday through Friday)

▶ Email [sales@onsetcomp.com](mailto:sales@onsetcomp.com)

▶ Call 1-508-759-9500

▶ In U.S. toll free 1-800-564-4377

▶ Fax 1-508-759-9100

Technical Support (8am to 6pm ET, Monday through Friday)

▶ Contact Product Support [www.onsetcomp.com/support/contact](http://www.onsetcomp.com/support/contact)

▶ Call 1-508-759-9500

▶ In U.S. toll free 1-877-564-4377

Onset Computer Corporation

470 MacArthur Boulevard

Bourne, MA 02532